

## MOTOR CHART

FAN	MOTOR CODE	HP	VOLTAGE/PHASE	SPEED	MOTOR #	STARTING AMPS	FULL LOAD	NAMEPLATES AMPS
DC/DCA	E	1/4	115/1	1S	#1751	26	3.3	3.2
DC/DCA	E	1/4	230/1	1S	#1796	15	1.4	1.3
DC/DCA	E	1/4	200/230/460/3	1S	#1755	7.4/6.4/3.2	1.6/1.4/3.72	1.3/1.2/6
DC/DCA	E	1/4	115/1	2S	#1759	23	4.4/2.8	4.2/2.7
DC/DCA/RC/RCA	F	1/3	115/230/1	1S	#2253	40/20	4.3/2.1	4.1/2.05
DC/DCA/RC/RCA	F	1/3	200/230/460/3	1S	#2255	8.5/7.4/3.7	1.61/1.4/71	1.55/1.4/70
DC/DCA	F	1/3	115/1	2S	#2250	30.5	6.0/3.3	5.7/3.2
DC/DCA	F	1/3	230/1	2S	#2251	15	3.1/1.5	3.1/1.4
DC/DCA/RC/RCA	G	1/2	115/230/1	1S	#2752	26/13	5.5/2.8	5.2/2.6
DC/DCA/RC/RCA	G	1/2	200/230/460/3	1S	#2754	12.9/11.2/5.6	2.5/2.2/1.1	2.2/1.1
DC/DCA	G	1/2	115/1	2S	#2757	45	8.0/3.7	7.6/3.6
DC/DCA	G	1/2	230/1	2S	#2758	22.5	4.0/2.0	3.8/1.9
DC/DCA	H	3/4	115/230/1	1S	#3253	71/35.5	7.9/4.0	7.6/3.8
DC/DCA	H	3/4	200/230/460/3	1S	#3255	17.3/15/7.5	3.2/2.8/1.4	2.7/1.35
DC/DCA	H	3/4	115/1	2S	#3259	57	11/6.6	10.6/6.0
DC/DCA	H	3/4	230/1	2S	#3260	28.5	5.5/3.1	5.3/3.0
DC/DCA	J	1	115/230/1	1S	#3785	66/33	12.0/6.0	11.4/5.7
DC/DCA	J	1	200/230/460/3	1S	#3760	20.2/17.6/8.8	4.1/3.6/1.8	3.6/3.4/1.7
DC	K	1-1/2	115/230/1	1S	#4561	100/50	15.4/7.7	14.8/7.4
DC	K	1-1/2	200/230/460/3	1S	#4510	33.6/16.8	5.06/2.53	4.9/4.8/2.4
*RC	D4	1/6-1/18	115/1	2S	#1511	3.3/1.8	1.7/1.6	1.7/1.6
RC	D4-2	1/8	115/1	1S	#1445	22	3.7	3.5
RC	E6	1/4	115/1	1S	#1750	5.5	2.75	2.6
RC	E6	1/4	230/1	1S	#1777	2.5	1.25	1.2
FCP	B2	1/3	115/1	VS	#1417	2.8	1.73	1.7
FCP	B2	1/3	230/1	VS	#1416	1.4	.81	.65
FCP/RCP/DDP	B4	1/10	115/230/1	VS	#1320	1.5	.66	1.2/60
FCP/RCP	F4	1/3	115/230/1	VS	#2204	5.4	2.31	4.1/2.05
FCP/RCP	G4	1/2	115/230/1	VS	#2740	7.1	2.75	5.2/2.6
*DDA/DDS	11	1/10	115/1	1S	#1116	3.7	2.6	2.6
DDA/DDS	E4	1/4	115/1	1S	#1768	7.5	3.1	3.0
DDA/DDS	E4	1/4	230/1	1S	#1770	4.3	1.7	1.5
DDA/DDS/AGD	F6	1/3	115/1	1S	#2274	12.0	5.0	4.6
DDA/DDS	F6	1/3	230/1	1S	#2275	6.3	2.6	2.3
*DDA	G8	1/2	230/1	1S	#2742	4.8	2.7	2.6
Dampner Motors #1424 115/1 180 Milli Amps Idle, 195 Milli Amps Stall #1629 230/1 95 Milli Amps Idle, 100 Milli Amps Stall								

\*Fasco Motors - all other data from G.E. Motors (but we might use Century or Baldor in addition to G.E. or Fasco for any of the above motors).



**ACME ENGINEERING & MANUFACTURING CORPORATION**  
MUSKOGEE, OKLAHOMA

## MOTOR CHART

FAN	MOTOR CODE	HP	VOLTAGE/PHASE	SPEED	MOTOR #	STARTING AMPS	FULL LOAD	NAMEPLATES AMPS
AGD	G8	1/2	115/230/1	1S	#2732	14.9/7.7		6.4/3.2
AGD/DDP/FCM	G6	1/2	115/230/1	VS	#2741	17.2/8.6	6.6/3.3	6.8/3.4
BDA	G	1/2	115/230/1	1S	#2752	26/13	5.5/2.8	5.2/2.6
	G	1/2	115/230/460/3	1S	#2754	12.9/11.2/5.6	2.5/2.8/1.1	2.2/1.1
	J	1	115/230/1	1S	#3785	66/33	12.0/6.0	11.4/5.7
	J	1	115/230/460/3	1S	#3760	20.2/17.6/8.8	4.1/3.6/1.8	3.6/3.4/1.7
DDP/FCM	F4	1/3	115/230/1	VS	#2205			
DDP/FCM	G6	1/2	115/230/1	VS	#2741			
Pad Pumps	10S	1/6	115/1					5.0
	15S	1/3	115/1					9.0
	30S	1/3	115/1					11.5
	60S	1/2	115/1					13.0
	30	1/3	115/208/230/1					8.0/4.0
	60	1/2	115/208/230/1					10.0/5.0



**ACME ENGINEERING & MANUFACTURING CORPORATION**  
**MUSKOGEE, OKLAHOMA**